

It enables the link with FD-300A and CCU.



Intercom Station

FD-800S

Accessory: AC cable, Rack Mount Kit

- Intercom
- All simul-con
- Maximum 2Km
- Alkaline Battery 50H
- Max. 10 sets connect

Mixing of recording sound is possible.

Mixing of recording sound to Intercom is possible by input it to NIX IN terminal. All persons using Intercom can hear the voice and sound for recording.

Main specifications:

Input/Output:
 Line: XLR-3pin (female) x5, BNC x3
 CCU: XLR-3pin (male) x5
 MIX IN: XLR-3pin (male) x2
 EXT-MIC IN: XLR-3pin (female) x2
 Size: 430x88x250mm (WxHxD)
 Weight: approx. 4kg
 Power: DC12V / AC
 Power consumption: approx. 15W

Max. 5 sets of CCU and 8 sets of FD-300A are connectable.

Maximum 5 sets of 2-wire Intercom of Sony CCU, CCU-D50/M5/M7, etc can be connected. Maximum 8 sets of FD-300A can be connected (Power can be supplied to maximum 5 sets). Rack mount hardware is supplied as standard accessory.

AC/DC can be used.

It can operate with AC and DC 12V for studio recording, event recording in the field (outside), etc.

Direct communication with CCU Intercom of other manufactures is possible.

Level adjustment and selection are easy by the input adjustment volume and output ON/OFF switch of each CCU. Pop-up volume is adapted to prevent mistake of operation.

Cable & Option

BND cables Connecting cables between FD-800S and FD-300A



MC-808 Flexible Microphone



CU-50 Connecting Cable
with Sony CCU-D50 (1m/4W)



CU-50 Connecting Cable
with CCU (1m/2W)

Please consult with us about the connection with other CCU.

BND Cable

Connecting cable between FD-800S and FD-300A (BNC, mini 4pin – Canon 3pin)

- BND-1M (1m)**
- BND-10M (10m)**
- BND-20M (20m)**
- BND-30M (30m)**
- BND-50M (50m)**
- BND-100M (100m)**

